

Radio MD360



Features >>

- Quiet, DC motor.
- Touch control technology, gently pulling the curtain to open or close the curtain.
- Intergrated control ensures operation of the curtain manually in case of power failure.
- Full automatic setting of the limits.
- Touch control function can be switched on and off.
- Built-in radio receiver, switch and/or network control.
- Easy to install, easy to operate.
- Compact aluminum track available for straight and curve curtains.
- Textile teeth belt is durable, can stand heavy curtains and frequent operations.

Parameters >>

Product Name	Rated Voltage	Rated Frequency	Rated Current	Rated Torque	Rated Speed	Speed	Insulation class	Protexion Index	Running Time
MD360-0.8D	24VDC	—	1.2A	0.8Nm	112rpm	0.16m/S	I.cl.E	IP41	S1
MD360-1.2D	24VDC	—	1.5A	1.2Nm	112rpm	0.16m/S	I.cl.E	IP41	S1
MD360-0.8A	100-240VAC	50/60Hz	0.8A	0.8Nm	112rpm	0.16m/S	I.cl.E	IP41	S1
MD360-1.2A	100-240VAC	50/60Hz	0.8A	1.2Nm	112rpm	0.16m/S	I.cl.E	IP41	S1

MD360-0.8D/MD360-1.2D Measurement: 265mm × 50.6mm × 60mm Net Weight: 1.19Kg	MD360-0.8A/MD360-1.2A Measurement: 305mm × 50.6mm × 60mm Net Weight: 1.4Kg
--	---

Load Capacity >>

MD360-0.8Nm with P322	4m	6m	8m	12m
	35Kg	30Kg	20Kg	
	25Kg	15Kg		

MD360-1.2Nm with P322	4m	6m	8m	12m
	50Kg	40Kg	30Kg	20Kg
	40Kg	30Kg	20Kg	
	25Kg	20Kg		

Accessories >>

	MD360-0.8A Motor 01353304 MD360-1.2A Motor 01353404 MD360-0.8D Motor 01352604 MD360-1.2D Motor 01352704		P322 Track 025350
			P322 Drive unit 025340
			Textile belt (10mm) 025517 Textile belt (11.5mm) 027783
	Master carrier 025133		Loop stop 025115
	Master carrier for curve track 025359		Loop stop for single operation 027743
	Master carrier 025339		Round bracket 025335
	P322 Runner 025351		Ceiling bracket 025318
	Wall bracket 025301		Track joiner 025349

Connection diagram >>

